




Box for wall mounting (on request)
IP64 protection rating

CODE

6 operating modes selectable and calibration by the customer	JOLLY2
4 operating modes selectable and calibration by the customer	JOLLY4

DESCRIPTION

- Weight indicator in DIN box suitable for panel mounting or in a box for wall mounting (on request).
- Dimensions: 96x96x65 mm (drilling template: 91x91 mm).
- 4-digit semi-alphanumeric red LED display (20 mm height).
- 8+3 signalling LED.
- 5-key keyboard.
- IP64 front panel protection rating.
- Removable screw terminal blocks.

INPUTS/OUTPUTS AND COMMUNICATION

- 2/4 relay digital outputs controlled by the setpoint values.
- 2 digital inputs.
- 1 load cell dedicated input.

MAIN FUNCTIONS

- Reading the load cells value expressed in mV: load cells connections continuous check.
- Digital filter to reduce the effects of weight oscillation.
- Theoretical calibration (via keyboard).
- Tare weight zero setting.

JOLLY4 weighing and batching systems; 4 modes selectable:

- Weight indicator with four alarm thresholds (4SET).
- Two products batching in loading with slow and cycle end (2LOAD).
- Three products batching in loading with cycle end (3LOAD).
- Four products batching in loading (4LOAD).

JOLLY2 weighing and batching systems; 6 modes selectable:

- Weight indicator with a relay alarm threshold (1SET)
- Weight indicator with two relay alarm thresholds (2SET)
- Single product batching in loading with two speeds (1LOAD)
- Two products batching in loading succession (2LOAD)
- Single product batching in unloading with two speeds (1UNLOAD)
- Two products batching in unloading succession (2UNLOAD)

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395) 279-98-46

Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12

Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Казахстан (772)734-952-31

Таджикистан (992)427-82-92-69

TECHNICAL FEATURES

Power supply and consumption	230 VAC; 50/60 Hz; 5 VA
Number of load cells • Load cells supply	up to 4 (350 Ω) • 5 VDC/60 mA
Internal divisions	20000
Measure range	-4 mV +16.5 mV
Display range	-999 +19999*
Display increments	x1 x2 x5
Conversion rate	10/s
Relay logic outputs	n. 2/4 - 115 VAC/2 A
Logic inputs	n. 2
Humidity (condensate free)	90%
Storage temperature	-20 °C +70 °C
Working temperature	-10 °C +50 °C

* over 10000 divisions the weight will restart from zero and will blink to indicate that the above mentioned value has been surpassed

OPTIONS ON REQUEST

	DESCRIPTION
	Power supply 12 VDC / 24 VDC
	IP64 box; dimensions 98x125x75 mm Wall mounting version

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395) 279-98-46

Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12

Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Казахстан (772)734-952-31

Таджикистан (992)427-82-92-69

Эл. почта mfd@nt-rt.ru || Сайт: <https://laumas.nt-rt.ru/>